

High Voltage LFP Battery User Manual SBR096/128/160/192/224/256



All Rights Reserved

All Rights Reserved

No part of this document can be reproduced in any form or by any means without the prior written permission of Sungrow Power Supply Co., Ltd (hereinafter "SUNGROW").

Trademarks

SUNGROW and other Sungrow trademarks used in this manual are owned by SUNGROW.

All other trademarks or registered trademarks mentioned in this manual are owned by their respective owners.

Software Licenses

- It is prohibited to use data contained in firmware or software developed by SUNGROW, in part or in full, for commercial purposes by any means.
- It is prohibited to perform reverse engineering, cracking, or any other operations that compromise the original program design of the software developed by SUNGROW.

About This Manual

The manual mainly describes the product information, guidelines for installation, operation and maintenance. The manual cannot include complete information the system (i. e. the PCS), just the battery. The reader can get additional information about other devices at **www.sungrowpower.com** or on the webpage of the respective component manufacturer.

Validity

This manual is valid for the following battery models:

- SBR096
- SBR128
- SBR160
- SBR192
- SBR224
- SBR256

They will be referred to as "battery" hereinafter unless otherwise specified.

Target Group

This manual is intended for battery owners who will have the ability to interact with the battery and qualified personnel who are responsible for the installation and commissioning of the battery. Qualified personnel should have the following skills:

- Training for installation and commissioning of electrical system, as well as dealing with hazards
- · Knowledge of the manual and other related documents
- Knowledge of the local regulations and directives

How to Use This Manual

Read the manual and other related documents before performing any work on the battery. Documents must be stored carefully and be available at all times.

Images in this manual are for reference only. The actual product received may differ.

Contents may be periodically updated or revised due to the product development. It is probably that there are changes of manual in the subsequent battery edition. The latest manual can be acquired via visiting the website at **support.sungrowpower.com**.

Symbols

Important instructions contained in this manual should be followed during installation, operation and maintenance of the PCS. They will be highlighted by the following symbols.

▲ DANGER

Indicates a hazard with a high level of risk that, if not avoided, will result in death or serious injury.

MARNING

Indicates a hazard with a medium level of risk that, if not avoided, could result in death or serious injury.

A CAUTION

Indicates a hazard with a low level of risk that, if not avoided, could result in minor or moderate injury.

NOTICE

Indicates a situation that, if not avoided, could result in equipment or property damage.



Indicates additional information, emphasized contents or tips that may be helpful, e.g. to help you solve problems or save time.

Abbreviation

BMS: Battery Management System
BMU: Battery Management Unit
CAN: Controller Area Network

CMU: Battery Cluster Management Unit

LFP: Lithium iron phosphate PCS: Power Conversion System

SOC: State of Charge

Contents

| ΑI | Rights Reserved | l |
|----|--|----|
| Αk | oout This Manual | II |
| 1 | Safety | 1 |
| | 1.1 Notices for Safe Use | 1 |
| | 1.2 Battery Handling Information | 2 |
| | 1.3 Emergency Situations | 3 |
| | 1.3.1 Leaking Batteries | 3 |
| | 1.3.2 Fire | 3 |
| | 1.3.3 Wet Batteries | 4 |
| | 1.3.4 Damaged Batteries | 4 |
| 2 | Product Description | 6 |
| | 2.1 Product Introduction | 6 |
| | 2.2 Terminal Description | 8 |
| | 2.3 Symbols on the Product | 9 |
| | 2.4 LED Indicator | 9 |
| 3 | Unpacking and Storage | 11 |
| | 3.1 Unpacking and Inspection | 11 |
| | 3.2 Scope of Delivery | 11 |
| | 3.3 Storage | 12 |
| 4 | Mounting | 14 |
| | 4.1 Safety during Mounting | 14 |
| | 4.2 Location Requirements | 14 |
| | 4.3 Installation Environment Requirements | 14 |
| | 4.4 Installation Clearance Requirements | |
| | 4.5 Installation Tools | 15 |
| | 4.6 PE Cable Preparation | 16 |
| | 4.7 Assembling the SUNCLIX Connector | 17 |
| | 4.8 Assembling the Communication Connector(Optional) | 18 |
| | 4.9 Installing the Battery | 20 |
| 5 | Parallel System (Optional) | 30 |
| | 5.1 Scope of Delivery | 30 |

| | 5.2 Mounting the Combiner Box | .31 |
|---|---|-----|
| | 5.3 Terminal Description (Combiner Box) | .31 |
| | 5.4 Connection Diagram in Parallel System | .32 |
| | 5.5 PE Cable Connection | .34 |
| | 5.6 Battery Connection | .34 |
| | 5.6.1 Assembling the Battery Connectors | .34 |
| | 5.6.2 Installing the Battery Connectors | .35 |
| | 5.7 SUNCLIX Connection | |
| | 5.8 COM2 Cable Connection | |
| | 5.8.1 Assembling the COM2 Cable Connector | .36 |
| | 5.8.2 Installing the COM2 Cable Connector | .38 |
| | 5.9 COM1 Cable Connection | .39 |
| 6 | Commissioning | .40 |
| | 6.1 Inspection before Commissioning | .40 |
| | 6.2 Commissioning Procedure | .40 |
| | 6.3 First Power-on Calibration | .41 |
| 7 | Decommissioning the Battery | .43 |
| 8 | Troubleshooting and Maintenance | .44 |
| | 8.1 Troubleshooting | .44 |
| | 8.2 Maintenance | .45 |
| 9 | Appendix | .47 |
| | 9.1 Technical Data | .47 |
| | 9.2 Quality Assurance | .50 |
| | 9.3 Contact Information | .51 |

1 Safety

The device has been designed and tested strictly according to international safety regulations. Read all safety instructions carefully prior to any work and observe them at all times when working on or with the device.

Incorrect operation or work may cause:

- · Injury or death to the operator or a third party;
- Damage to the device and other properties.

All detailed work-related safety warnings and notes are specified at critical points in this manual.

- The safety instructions in this manual cannot cover all the precautions that should be followed. Perform operations considering actual onsite conditions.
- A
- SUNGROW shall not be held liable for any damage caused by violation of the safety instructions in this manual.
- When installing, operating, and maintaining the device, comply with local laws and regulations. The safety precautions in this manual are only supplements to local laws and regulations.

1.1 Notices for Safe Use

Read all safety instructions carefully prior to any work and observe them at all times when working on or with the battery. Failure to observe the precautions described in this section can cause serious injury to persons or damage to property.

A DANGER

Risk of explosion

- Do not subject the battery to any strong force.
- Do not mechanically damage the battery (pierce, deform, strip down, etc.)
- · Do not heat the battery or dispose of the battery in a fire.
- Do not install the battery in potentially explosive environments.
- · Do not place the battery in water or other liquids.

1 Safety User Manual

A DANGER

Risk of fire

• Do not place the battery near a heat source, such as direct sunlight, a fireplace, a thermally uninsulated wall exposed to sunlight, hot water, or a heater.

 Keep sources of ignition such as sparks, flames, and smoking materials away from the battery.

A DANGER

Risk of electric shock

- Do not disassemble the battery.
- Do not handle a wet battery or use wet tools.
- · Do not soak the battery in water or expose it to moisture or liquids.
- Keep the battery away from children and animals.
- Wear suitable clothing, guards and gloves to prevent you from direct contact with the DC voltage.
- · Use insulated tools during working with battery.
- Set aside metal jewelry before working on the DC circuit.

1.2 Battery Handling Information

NOTICE

Comply with local standards for use with the battery.

Any man-made damage will void the limited warranty for the battery. Handle the battery with care to protect it from damage.

- Use the battery only as intended and designed.
- The battery must only be installed at a suitable location.
- Make sure the battery is well connected to ground before use.
- Do not use the battery if it is defective, appears cracked, broken or damaged, or fails to operate.
- Do not use the battery together with other types of batteries.
- Do not pull, drag or step on the battery.
- · Do not leave any foreign objects inside the battery.
- Do not repair or modify the battery. It is not user serviceable.
- Do not pull out any cables when the battery is powered on.

User Manual 1 Safety

- Do not damage the sheath of cables, wire harness and connectors.
- While the battery is charged, used and stored, keep it away from materials that are prone
 to electric discharge, including static discharge.
- Keep the battery away from babies and children to avoid any accidents.
- · Cover terminals with insulating tape before proper disposal.
- Avoid direct contact with rain, snow, and water, and prevent the battery from falling and mechanical impact during battery transportation.

1.3 Emergency Situations

1.3.1 Leaking Batteries

Abuse/misuse/damage of the battery may cause increasing of internal pressure in the battery cells. It may result in the electrolyte venting. In the event that battery electrolyte is released:

- Do not enter the room under any circumstance.
- Avoid contact with the leaking liquid or gas.
- · Call the Local Emergency number or Fire Brigade if necessary.

If one is exposed to the leaking substance, follow the suggestions below to minimize the chance of injury:

- Inhalation: Evacuate the contaminated area, and seek medical aid.
- Eye contact: Rinse eyes with copious amounts of water for at least 15 minutes, and seek medical aid immediately.
- Skin contact: Wash the affected area thoroughly with plenty of water for at least 15 minutes. If possible, remove or saturate contaminated clothing with water. Seek medical aid if the patient is distressed.
- · Ingestion: Induce vomiting, and seek medical aid immediately.

Wipe out the contacted area with a sponge or cloth that is soaked in water until you obtain medical aid. These materials can damage skin and eyes, causing blindness.

1.3.2 Fire

Fire may occur with the battery despite its careful design. Likewise, a fire or unusually high temperatures near the battery can cause it to catch fire.

Protective equipment

A respirator is not required during normal operations.

In the event of a fire, hazardous fumes including carbon monoxide, carbon dioxide, and/or various hydrocarbons may be emitted. To comply with the Personal Protective Equipment Directive (89/686/EEC), use a full-face self-contained breathing apparatus (SCBA) with full protective gear during fire fighting.



1 Safety User Manual

Fire fighting

NOTICE

In the event of a fire, only qualified firefighters with appropriate protective equipment are permitted to enter the room where the battery is located.

It may take a long time to completely extinguish the fire. Consider allowing the system to burn. Smoke indicates that the battery is still burning. Always note that there is a risk of the battery re-igniting.

Proceed as follows for fire-fighting.

- 1 Shut off any connected power system or electronics such as the battery, battery isolator, PV DC isolator(s), AC isolator, solar supply main switch and normal supply main switch.
- 2 Perform an adequate knock down on the fire before entering the incident's hot zone.
- 3 If the battery catches on fire, use fire-fighting sand, CO₂ extinguisher, or other emergency fire extinguishing equipment approved by fire fighters to extinguish the fire.
- 4 If the fire is not from the battery and has not spread to it yet, use an ABC fire extinguisher to extinguish the fire. Remove batteries and other ignition sources from the scene of a fire.

1.3.3 Wet Batteries

If the battery is submerged in water, do not let people access it, and then contact Sungrow or an authorized service partner for technical support.

If a battery is submerged in water or flooded, first, switch off all circuit breakers in the system to cut off the power supply to the battery. Wait until floodwaters subside and do not approach near battery. If someone needs to go into the flooded water, wear insulated full length rubber boots and gloves.

Do not use a flooded battery again.

1.3.4 Damaged Batteries

The battery consists of lithium-ion cells. These are considered dry cell batteries. If the battery is damaged, only a small amount of battery fluid can leak.

A damaged battery can cause rapid heating of the battery cells. If you notice smoke coming from the battery area, assume that the battery is burning and take appropriate action as described in "1.3.2 Fire".

Damaged batteries are dangerous and must be handled with extreme caution. They are not fit for use and may pose a danger to people or property. If a battery seems to be damaged:

- 1 Pack it in its original container.
- 2 Store it in a separated room like the installation place.
- 3 Contact SUNGROW.

User Manual 1 Safety

▲ DANGER

A damaged battery may release dangerous material and a flammable gas mixture. Never try to repair the battery even if you are a qualified electrician.

2 Product Description

2.1 Product Introduction

Brief Introduction

The battery is designed for residential energy storage systems. The inbuilt battery management system monitors its operation and prevents the battery from operating beyond the specified limitations.

This product is a high-voltage battery system with an operating voltage range between 150 V \sim 584 V. A battery system consist of 3 to 8 individual battery modules connected in series. Max.4 batteries can be connected in parallel to compatible PCS. Please refer to PCS man-

Max.4 batteries can be connected in parallel to compatible PCS. Please refer to PCS manual for the compatibility details.




figure 2-1 Product overview




Images are for reference only. The actual products received may differ.

User Manual 2 Product Description

table 2-1 Design of the product

| Position | Designation |
|----------|--|
| | LED Indicator |
| | LED indicator include the SOC indicator and the status indicator. The status |
| Α | indicator is also used as the power button. |
| | LED indicator indicates the SOC value and status of the battery. |
| | Nameplate |
| | The nameplate clearly indentifies the product. The nameplate must remain |
| | permanently attached to the product. You will find the following information |
| В | on the nameplate: |
| J | SUNGROW logo and product model |
| | Technical data |
| | Product symbol |
| С | DC circuit breaker |

Major Components





Images are for reference only. The actual products received may differ.

| Name | Designation | Designation | |
|------|----------------|-------------|--|
| A | Base | | |
| В | Battery module | | |
| С | Top cover | | |
| D | Switch gear | | |
| E | Side cover | | |


2 Product Description User Manual

Configuration Table

| No. | Model | Base | Battery module | Top cover | Switch gear | Side cover |
|-----|--------|------|-------------------|-----------|-------------|------------|
| 1 | SBR096 | 1 | 3 | 1 | 1 | - |
| 2 | SBR128 | 1 | 4 | 1 | 1 | 1 |
| 3 | SBR160 | 1 | 5 | 1 | 1 | 2 |
| 4 | SBR192 | 1 | 6 | 1 | 1 | 3 |
| 5 | SBR224 | 1 | 7 | 1 | 1 | 4 |
| 6 | SBR256 | 1 | 8 | 1 | 1 | 5 |

2.2 Terminal Description

All electrical terminals are located at the switch gear.





Images are for reference only. The actual products received may differ.

| No. | Label | Description |
|--------|---|--|
| 1 P- | | The system negative terminal, connected to the PCS nega- |
| | 1 - | tive terminal |
| 2 | P+ | The system positive terminal, connected to the PCS positive |
| 2 FT | | terminal |
| 3 COMM | To enable the communication between the PCS and the | |
| J | COMM | battery |
| 4 | = | Grounding terminal, connected to the ground |
| 5 | DC circuit | To connect/disconnect the DC circuit, for power-on, power-off, |
| J | breaker | and short-circuit protection |
| | | |

User Manual 2 Product Description

2.3 Symbols on the Product

| Symbol | Explanation |
|--------------------------|--|
| \wedge | Pay attention to the danger. Do not operate this product in the live |
| | status! |
| | No open flames |
| | Do not expose to flame, incinerate, puncture, or impact. |
| \wedge | Electric shock hazard |
| 4 | Serviced by qualified personnel only. Out of reach from children. |
| TÜVRheinland GERTIFED | TÜV mark of conformity |
| TUV | TÜV mark of conformity |
| CE | CE mark of conformity |
| A | Do not dispose in trash. |
| / 3 | Compacting a lithium ion battery is dangerous as it can explode. |
| | Please recycle this lithium ion battery. Do not discard. |
| i | Read the user manual before maintenance! |
| | This is a protective grounding terminal, which should be grounded securely to protect the safety of operators. |

2.4 LED Indicator

LED indicators include the SOC indicator and the status indicator. The status indicator is also used as the power button.

SOC Indicator

The SOC indicator indicates the current SOC value of the battery. One bar indicates the SOC value of 10%.



Status Indicator

The Status indicator indicates the current state of the battery.

2 Product Description User Manual

| LED color | LED indicator | LED state | Definition | |
|-----------|---------------|---------------|---|--|
| | | ON | Normal operation (without fault) | |
| | Blue | Slow blink | The battery is at power-on or standby state | |
| | | Period: 2 s | (without fault). | |
| | | Fast blink | The battery is at firmware update state. | |
| | | Period: 0.5 s | The battery is at infilware update state. | |
| | | ON | A system fault has occured. | |
| | Red | Blink | The battery is at power-on or standby state | |
| | | | (with primary fault). | |



Images are for reference only. The actual products received may differ.

The status indicator can be used to power on or off the battery.

| Operation | Definition |
|--|--------------------------|
| Press and hold for less than 2 seconds | To power on the battery* |
| Press and hold for more than 4 seconds | To power off the battery |

NOTICE

*The start mode is black start, please refer to "6.2 Commissioning Procedure" for details.

3 Unpacking and Storage

3.1 Unpacking and Inspection


The device is thoroughly tested and strictly inspected before delivery. Nonetheless, damage may still occur during shipping. For this reason, please conduct a thorough inspection after receiving the device.

- · Check the packing case for any visible damage.
- · Check the scope of delivery for completeness according to the packing list.
- · Check the inner contents for damage after unpacking.

Contact SUNGROW or the transport company in case of any damage or incompleteness, and provide photos to facilitate services.

Do not dispose of the original packing case. It is recommended to store the device in the original packing case when the device is decommissioned.

3.2 Scope of Delivery



| Item | Name | Quantity |
|------|--------------------------------------|----------|
| A | Base | 1 |
| В | Battery module | 3~8 |
| С | Top cover | 1 |
| D | Switch gear | 1 |
| E | Bracket | 1 |
| F | Side cover | 3 ~ 8 |
| G | Communication connector | 1 |
| Н | M5*125 hex socket screw (optional) | 1 |

| Item | Name | Quantity | |
|------|------------------------|----------|--|
| 1 | Foot | 4 | |
| J | M5*14 hex socket screw | 18 | |
| K | Expansion plug set | 2 | |
| L | M5 screw sets | 3~6 | |
| M | M6 fender washer | 2~4 | |
| N | Stud(optional) | 1 | |
| 0 | SUNCLIX connector | 1 | |
| Р | OT terminal | 1 | |
| Q | Documents | 1 | |

Images are for reference only. The actual products received may differ.

If the top cover is C1, you will received M5*125 hex socket screws. If the top cover is C2, you will receive stud.



Please refer to the installation diagram for the specific quantity of fasteners used.

There are some differences in appearance of current products, as shown in the figure above: 1 or 2. The products with the two appearances are shipped randomly, you may receive 1 or 2.

3.3 Storage

Proper storage is required if the battery is not installed immediately.

- · Store the battery in the original packing case with the desiccant inside.
- Preferably, keep the temperature in the range of 15°C to 25°C. Store the battery within the temperature range of -10°C to 35°C for no more than 6 months.
- The storage relative humidity must be always between 0 and 95%, non-condensing.
- Store the battery in a clean and dry place, without exposure to sunlight and rain. The storage location must be free of harmful gases, flammable/explosive products and corrosive chemicals. The battery should be prevented from mechanical impact, high pressure, high-intensity magnetic field and direct exposure to sunlight.
- Pay attention to the harsh environment, such as sudden cooling/heating and collision, to avoid damage to the battery.
- The number of stacking layers of battery modules with package must not exceed 6. It is strictly forbidden to directly stack batteries without package.
- Regularly inspect the package for damage and insect bites. If any damage is found, the
 product should be replaced immediately.
- · The packing should be upright.
- If stored for more than 6 months under the specified conditions, the battery needs to be charged once, until the system SOC is 50% to 80%. Preferably, use an PCS for forced charging.

User Manual 3 Unpacking and Storage



If the battery is stored over one year, 5%~10% of the capacity may lose irreversibly.



4 Mounting

4.1 Safety during Mounting

MARNING

This product or system must be operated by professionals!

Failure to follow the safety instructions in this manual or operation of this product or system by non-professionals may cause severe personal injury or major property damage.

M WARNING

Strictly follow local relevant standards and requirements in the whole process of installation.

4.2 Location Requirements

Select an optimal mounting location for safe operation, long service life and expected performance.

The battery with IP55 can be installed both indoors and outdoors.


Install the battery in a place convenient for electrical connection, operation, and maintenance.

4.3 Installation Environment Requirements

- The installation environment must be free of inflammable or explosive materials.
- · The location should be not accessible to children.
- The ambient temperature is recommended to be between 10°C and 30°C. Please refer to "9.1 Technical Data" for the maximum operation temperature range.
- The relative humidity must be always between 0 and 95%, non-condensing.
- · Avoid direct exposure to sun, rain and snow.
- The battery should be well ventilated. Ensure air circulation.

4.4 Installation Clearance Requirements

 Reserve enough clearance around the battery to ensure sufficient space for heat dissipation.



• In case of multiple batteries, reserve specific clearance between the batteries.



4.5 Installation Tools

Installation tools include but are not limited to the following recommended ones. If necessary, use other auxiliary tools on site.

table 4-1 Tool specification



Goggles



Dust mask



Protective gloves



Insulated shoes




4.6 PE Cable Preparation

Additional grounding cable is prepared by customers.

table 4-2 Cable requirements

| Туре | Specification |
|---|---------------|
| Complying with 1000V and 105°C standard | 4–6 mm² |

step 1 Prepare the cable and OT/DT terminal.



- - End

4.7 Assembling the SUNCLIX Connector

NOTICE

During assembly, be careful not to contaminate, pull out, or shift, the seal in the cable gland. A contaminated or shifted seal impairs strain relief and leak tightness.






figure 4-1 SUNCLIX Connector Components

- 1: Spring
- 2: Sleeve
- 3: Insert
- 4: Cable gland


step 1 Strip the insulation from the cable by $10 \sim 15$ mm.




step 2 Pry the connection open and pull the sleeve and the insert apart.



step 3 Insert the stripped cable into the cable gland up to the stop. The stranded wire can be seen inside the spring. Press the spring down until it audibly snaps into place.



step 4 Push the insert into the sleeve and tighten the cable gland (torque 2 N·m).



- - End

4.8 Assembling the Communication Connector(Optional)




If the communication connector received is G2, please skip this step.


step 1 Unscrew the swivel nut from the connector.



step 2 Remove the inner rubber gasket.



step 3 Insert the RJ45 plug into the front plug connector until there is an audible click, and install the rubber gasket.



step 4 Tighten the swivel nut.



- - End

4.9 Installing the Battery


Assemble the battery on a flat surface.

A

The SBR128 mounting will be used as an example.

The product with base A1 is taken as an example in the following installation steps.

step 1 Install the feet of the battery.



step 2 Align the base with the wall, and keep a distance of 30 mm to 45 mm between the base and the wall. Mark the hole positions of the mounting bracket with a marker according to the required layout of holes.

Case 1: The base is A1.




figure 4-2 Layout of holes with the base A1 as reference

A: Upper surface of the base

B: Base A1(front view)

C: Measurement baseline

D: Base A1(top view)



Mark the hole positions along a line vertical to the measurement baseline.

The feet of the base have been installed already.

Case 2: The base is A2.




figure 4-3 Layout of holes with the base A2 as reference

A: Upper surface of the base


B: Base A2(front view)

C: Base A2(top view)



The feet of the base have been installed already.


step 3 Drill the holes according to the marked positions, and install the expansion sleeves.




NOTICE

Goggles and gloves are necessary when drilling holes for protection. Shield the battery during drilling. After drilling, clean up debris in time.

step 4 Position the base maintaining the required distance from the wall.




step 5 Place each battery module on top of the base.




When carrying the battery module, always be aware of its weight of 33 kg.

step 6 Fix the battery modules with the included screws.



step 7 Connect the switch gear to the base.




1

Ensure that the DC circuit breaker is disconnected.


step 8 Fix the switch gear with the provided M5 screw or stud.

The installation varies for products with different top covers. The product received shall prevail.

Case 1: The top cover is C1.



Case 2: The top cover is C2.







When 4 or more than 4 battery modules are installed in one base, M5 screw set is required to secure the switch gear. The stud is mounted on the top of battery module.

step 9 Fix the battery to the wall.

Case 1: The bracket is E1.



Case 2: The bracket is E2




The bracket is mounted on the top battery module.



The mounting position can be fine-tuned through oval holes in the back.

Goggles and gloves are necessary when drilling holes for protection. Shield the battery during drilling. After drilling, clean up debris in time.

step 10 Connect the harness.






The installation method of communication connector G1 and communication connector G2 is the same, and here takes G1 as an example.

For communication between the battery and the PCS. Connect the communication cable from the "COMM" terminal of the battery to the PCS. Strip the insulation layer of the communication cable with a wire stripper, and lead the corresponding CAN1_H/CAN1_L signal cable out. Cut off the redundant signal cable and warp it with a heat-shrink tubing. Signal cable 1 white and orange cable is used as CAN1_H; and signal cable 2 orange cable is used as CAN1_L.



NOTICE


Please ensure that the SUNCLIX cable are connected to same terminals, as shown below.




step 11 Place the top cover and fix it with the screws provided.

The installation varies for products with different top covers. The product received shall prevail.

Case 1: The top cover is C1.




Case 2: The top cover is C2.





The product with C1 is taken as an example in the following installation steps.

step 12 (Optional) Install the side covers.



User Manual 4 Mounting



When 4 or more than 4 battery modules are installed in one base, side covers are required.


- - End



5 Parallel System (Optional)

Max.4 batteries can be connected in parallel to compatible PCS. Please refer to PCS manual for the compatibility details.

5.1 Scope of Delivery




| Item | Name | Quantity |
|------|--------------------|----------|
| Α | Combiner box | 1 |
| В | Bracket | 1 |
| С | Expansion plug set | 3 |
| D | M4 screw set | 1 |
| E | COM2 connector | 1 |
| F | SUNCLIX connector | 1 |
| G | COM1 connector | 1 |
| Н | Battery connectors | 4 |
| 1 | OT terminal | 1 |
| J | M6 screw set | 5 |
| K | Mounting ear | 1 |
| L | Cord-end terminal | 18 |

^{*} Images are for reference only. The actual products received may differ.

5.2 Mounting the Combiner Box

step 1 Install the wall-mounting bracket and mount the Combiner box to the bracket.



- - End

5.3 Terminal Description (Combiner Box)

All electrical terminals are located at the bottom of the combiner box.




figure 5-1 Terminals at the Bottom of the Combiner Box

table 5-1 The label description of Combiner Box terminal

| No. | Label | Description |
|-----|--------------|---|
| | BAT1+, BAT1- | |
| 1 | BAT2+, BAT2- | BAT+ terminals, connected to the battery P+ terminal |
| ı | BAT3+, BAT3- | BAT- terminals, connected to the battery P– terminal |
| | BAT4+, BAT4- | |
| 2 | COM1 | Communication terminal, connected to the PCS communica- |
| | CONT | tion terminal |

^{*} The image shown here is for reference only. The actual product received may differ.


| No. | Label | D | escription |) | | | | |
|--------------------------------------|---------|-------------------------|---|-------------|-------------|------------|-----------|-------|
| 3 | 2 00140 | | ommunica | tion termin | al, connec | ted to the | battery C | ОММ |
| | COM2 | te | erminal | | | | | |
| 4 | D. D | Р | + terminal, | connected | I to the PC | S positive | terminal | |
| 4 | P+, P– | | P- terminal, connected to the PCS negative terminal | | | d | | |
| 5 | | Connected to the ground | | | | | | |
| table 5-2 The label of COM2 terminal | | | | | | | | |
| L1 | 1 L2 | L1 | L2 | L1 | L2 | L1 | L2 | Α |
| H ² | 1 H2 | H1 | H2 | H1 | H2 | H1 | H2 | В |
| В | MS1/CAN | BMS | 2/CAN | BMS3 | /CAN | BMS4 | I/CAN | RS485 |

table 5-3 The label description of COM terminal


| No. | Label | Description | |
|-----|---------------------------|--|--|
| | BMS1/CAN (L1, L2, H1, H2) | | |
| 4 | BMS2/CAN (L1, L2, H1, H2) | One was to day the heaten a COMMA consideral | |
| 1 | BMS3/CAN (L1, L2, H1, H2) | Connected to the battery COMM terminal. | |
| | BMS4/CAN (L1, L2, H1, H2) | | |
| 2 | RS485 (A, B) | Connected to the BMS, functionally | |
| 4 | 110-100 (11, D) | reserved. | |

5.4 Connection Diagram in Parallel System

Maximum four batteries can be connected in parallel.



 The COMM terminal of the battery is connected to the COM2 terminal of the combiner box. Signal cable 1 white and orange cable is used as BMS/CAN_H1; signal cable 2 orange cable is used as BMS/CAN_L1; signal cable 5 white and blue cable is used as BMS/CAN_H2; and signal cable 6 green cable is used as BMS/CAN_L2.




- The grounding terminal of the battery is connected to the PE terminal of the combiner box.
- The COM1 terminal of the combiner box is connected to the PCS. Signal cable 1 white
 and orange cable is used as CAN1_H; and signal cable 2 orange cable is used as
 CAN1_L.



5.5 PE Cable Connection

- step 1 For the preparation of PE cable, refer to section "4.6 PE Cable Preparation".
- step 2 Remove the screw on the **PE** terminal and fasten the cable with a screwdriver.




step 3 Apply paint to the grounding terminal to ensure corrosion resistance.

--End


5.6 Battery Connection

5.6.1 Assembling the Battery Connectors

step 1 Strip the insulation from each DC cable by 7 ~ 8 mm.



step 2 Assemble the cable ends with the crimping pliers.



1: Positive crimp contact

2: Negative crimp contact

step 3 Lead the cable through cable gland, and insert the crimp contact into the insulator until it snaps into place. Gently pull the cable backward to ensure firm connection. Tighten the cable gland and the insulator (torque 2.5 N.m to 3 N.m).




step 4 Check for polarity correctness.

--End

5.6.2 Installing the Battery Connectors

step 1 Connect the Battery connectors to corresponding terminals until there is an audible click.




step 2 Seal the unused Battery terminals with the terminal caps.


- - End

5.7 SUNCLIX Connection

- step 1 For the assembly of the SUNCLIX connector, refer to the section"4.7 Assembling the SUN-CLIX Connector".
- step 2 Remove the waterproof lid from **P+** and **P-** the terminal.



step 3 Plug the connectors into P+ and P- terminals.



step 4 Ensure that the connectors are securely in place.


- - End

5.8 COM2 Cable Connection


5.8.1 Assembling the COM2 Cable Connector

The BMS3/CAN terminal is used as an example for description.


step 1 Unscrew the swivel nut from the connector.




step 2 Take out the terminal block.




step 3 Remove the seal and lead the cable through the cable gland.




step 4 Strip the cable with a wire stripper.




step 5 Crimp the cord end terminal.




step 6 Plug the wires into the corresponding terminal according the labels on the bottom of the device.



- step 7 Pull the wires outward to check whether they are firmly installed.
- step 8 Insert the terminal block into the connector until it snaps into place with an audible click.




step 9 Fasten the swivel nut.




- - End

5.8.2 Installing the COM2 Cable Connector

step 1 Remove the waterproof lid from the **COM2** terminal.



step 2 Insert the COM2 connector into **COM2** terminal on the bottom of the combiner box until there is an audible click.



step 3 Pull cables outwards to confirm whether they are fastened firmly.

--End


5.9 COM1 Cable Connection

step 1 For the assembly of the COM1 connector, refer to the section"4.8 Assembling the Communication Connector(Optional)".



If the COM1 connector received is G2, please skip this step.

step 2 Insert the COM1 connector into **COM1** terminal on the bottom of the combiner box. Tighten the swivel nut.





The installation method of COM1 connector G1 and COM1 connector G2 is the same, and here takes G1 as an example.

- - End

6 Commissioning

6.1 Inspection before Commissioning


Check the following items before starting the battery:

- · Check that the battery system has been installed completely.
- · Check that the appearance of the battery system is intact.
- Check that the battery system output wiring harness is correctly connected to the positive and negative terminals of the battery and PCS to avoid misconnection and reverse connection.
- If a combiner box is used, check whether the connection between the battery and the combiner box and the connection between the combiner box and the PCS is complete, and whether the positive and negative terminals are correctly connected.

6.2 Commissioning Procedure

If all of the items mentioned above meet the requirements, proceed as follows to start up the battery for the first time.

- step 1 Connect all the switches on the AC and DC sides of the PCS.
- step 2 Manually connect the DC breakerand AC breaker on the right side of the battery so that the BMS enters the self-test state. The status indicator blinks in blue. Wait until the indicator is steady on in blue, which indicates that the battery system is powered on and runs normally.




User Manual 6 Commissioning

Black Start:



If the communication is established for the first time between the battery and the PCS, and the PCS has no DC power supply and no AC power supply: Manually connect the DC breaker on the right side of the battery so that the BMS enters the self-test state. The status indicator blinks in blue. Ten seconds later, press and hold the status indicator for less than 2 seconds. Wait until the indicator is steady on in blue, which indicates that the battery system is powered on and runs normally.

step 3 Close the protective cover.



- - End

M WARNING

During commissioning, if there is a short-circuit fault in the battery system, disconnect the power cable between the switch gear and the PCS, check the battery system wiring, and eliminate the short-circuit fault point. Execute step 2, check whether there is a fault in the battery (the indicator light is red), and obtain fault information through iSolarCloud to contact SUNGROW to repair the battery system.

6.3 First Power-on Calibration

NOTICE

The battery can only be connected to PCS produced by SUNGROW, as listed below:

- Three-phase model: SH5.0RT, SH6.0RT, SH8.0RT, SH10RT.
- Single-phase model: SH3.0RS, SH3.6RS, SH4.0RS, SH5.0RS, SH6.0RS.



Pay attention the PCS firmware version should be same that is illustrated in PCS manuals.

6 Commissioning User Manual



When the battery works with PCS, it automatically calibrates every half year. Calibration is done automatically by batteries and PCS given that there is electricity in the grid or PV modules to charge and discharge batteries.

step 1 The battery automatically issues discharge instructions to PCS, which discharge the battery to 0% SOC at rated current.

step 2 PCS charges the battery to 100% the capacity to complete the calibration of battery capacity and SOH.

--End

NOTICE

During calibration, the discharge cut-off function and charge-discharge current limiting function are disabled.



7 Decommissioning the Battery

Decommission the battery in the system after the PCS is decommissioned. Proceed as follows to decommission the battery.

- step 1 Press and hold the power button for 4 seconds until the DC breaker on the right side of the battery is disconnected.
- step 2 One minute after the DC breaker is disconnected, disconnect all cables between the battery and other devices.
 - - End



Contact SUNGROW to dispose of the battery.

M WARNING

If a combiner box is used, power off the DC and AC sides of the PCS, and disconnect MCBs of all battery RACKs before operating the battery system.



8 Troubleshooting and Maintenance

8.1 Troubleshooting

Once the battery fails, the fault information can be displayed on the App interface. If the PCS is equipped with an LCD screen, the fault information can be viewed on it. The fault codes and troubleshooting methods of all battery are detailed in the table below. The device you purchase may only contain some of the fault information, and when the battery fails, you can check the corresponding information through the fault codes from the mobile App.

| Alarm ID | Alarm Name | Corrective Measures |
|--|------------------|---|
| 703, 707, 708, 711, 712, 715, 717, 732– 737, 739, 832–837, 839, 844, 864, 866– 868, 870 | Battery fault | In case of abnormal battery voltage, check whether the battery power cable connection is abnormal (reverse connection, loose, etc.). If so, correct it to ensure reliable connection. Check whether the battery real-time voltage is abnormal if the battery power cable is correctly connected. If so, contact the battery manufacturer. If not, contact SUNGROW. In case of abnormal battery temperature, take measures to change the ambient temperature, such as improving heat dissipation conditions. |
| | | If the fault persists, contact battery manufacturer. |
| 932–935, 937, 939, 964 | Battery alarm | Generally, the battery can automatically recover. In case the alarm persist for a long time: 1. If the alarm is caused by ambient temperature, such as over temperature alarm or low temperature alarm, take measures to change the ambient temperature, such as improving heat dissipation conditions. 2. If the fault persists, contact battery manufacturer. |

8.2 Maintenance

NOTICE

When adding new battery modules for capacity expansion, please contact SUN-GROW and follow the instruction released by SUNGROW. Otherwise, the system performance will be affected or even cannot operate properly.

Below is the recommended maintenance cycle. The actual maintenance cycle should be adjusted according to the specific installation environment of this product.

The power station scale, installation location and on-site environment affect the maintenance cycle of this product. In sandy or dusty environments, it is necessary to shorten the maintenance cycle and increase the frequency of maintenance.

Maintenance performed once a year

| Inspection item | Inspection method | | |
|---------------------------------------|---|--|--|
| | Check the following items. In case of nonconformity, take corrective actions immediately: | | |
| | Check the battery module and internal devices for damage or deformation. | | |
| Battery module status and cleanliness | Check the internal devices for abnormal noise during operation. | | |
| | Check whether the temperature inside the battery RACK is too high. | | |
| | Check whether the internal humidity and dust of the battery module are within the normal ranges. If necessary, clean the battery module. | | |
| Warning sign | Check whether the warning sign and label are legible | | |
| Warning sign | and dirty. If necessary, clean them. | | |
| Wire and cable | Check whether the switch gear and PCS are con- | | |
| vvire and cable | nected correctly. | | |
| Corrosion | Check the battery module for internal oxidation or | | |
| Corrosion | rust. | | |



Maintenance performed once every six months

| Inspection item | Inspection method | | |
|-------------------------|---|--|--|
| | Check the following items. In case of nonconformity, take corrective actions immediately: | | |
| Switch gear and battery | Check whether there are flammable objects around the battery module. | | |
| module | Check whether the battery module is reliably fixed on the wall, and whether any fixing point is corroded. | | |
| | Check the switch gear and battery module for damage, paint peeling, oxidation, etc. | | |
| | The inspection must not be carried out until all internal de- | | |
| | vices of the battery module are powered off! | | |
| | In case of nonconformity found in inspection, take correc- | | |
| | tive actions immediately: | | |
| Wire and cable layout | Check the cable layout for short circuit and compliance with the specifications. If case of any abnormality, take corrective actions immediately. | | |
| | Check the battery module for internal seepage of water. | | |
| | Check whether the cables are loose, and tighten them according to the aforesaid torque. | | |
| Grounding | Check whether the grounding is correct. | | |
| | Check whether the current, voltage and temperature in | | |
| Function inspection | the operation record of the battery module are within the | | |
| | operating ranges. | | |

NOTICE

The battery capacity can be automatically calibrated, and it is supported only by the Sungrow PCS system.

9 Appendix

9.1 Technical Data

table 9-1 Technical parameters of high voltage LFP battery(SBR096 / SBR128 / SBR160).

| Parameters | SBR096 | SBR128 | SBR160 | |
|-------------------|------------------------|----------------------------|--------------|--|
| System Data | | | | |
| Battery Type | LiFePO4 Prismatic Cell | | | |
| Battery | 2.0.14M/s. 20.1 | | | |
| Module | | 3.2 kWh, 33 kg | | |
| Energy (usa- | 0.6144/b | 40.0 1/1/1/15 | 40 141/14 | |
| ble) ¹ | 9.6 kWh | 12.8 kWh | 16 kWh | |
| Nominal | 4001/ | 0501/ | 000.17 | |
| voltage | 192 V | 256 V | 320 V | |
| Operating | | | | |
| voltage | 150 V– 219 V | 200 V– 292 V | 250 V– 365 V | |
| Rated DC | | | | |
| power | 5.76 kW | 7.68 kW | 9.60 kW | |
| Max. charge/ | | | | |
| discharge | 6.57 kW | 8.76 kW | 10.95 kW | |
| power | | | | |
| Max. charging | | | | |
| / discharging | | | | |
| current: | 30 A | | | |
| continuous | | | | |
| Max. charging | | | | |
| / discharging | | 42 A | | |
| current: | 42 A | | | |
| Depth of | | | | |
| Discharge | | Max. 100% DOD(settab | ole) | |
| Short circuit | | | | |
| current | | 3500 A | | |
| Display | | SOC indicator, Status indi | icator | |
| Communica- | | | | |
| tion interface | CAN | | | |
| Protection | | | | |
| Over / under | | | | |
| voltage | Yes | | | |
| protection | | | | |

9 Appendix User Manual

| Parameters | SBR096 | SBR128 | SBR160 | |
|-----------------------|---|-----------------------|-----------------|--|
| Over current | | Yes | | |
| protection | | res | | |
| Over / under | | | | |
| temperature | | Yes | | |
| protection | | | | |
| DC breaker | | Yes | | |
| General Data | | | | |
| Dimensions | 625 * 545 * 330 | 625 * 675 * 330 | 625 * 805 * 330 | |
| (W*H*D) | mm | mm | mm | |
| Weight | 114 kg | 147 kg | 180 kg | |
| Installation | | Indoor / Outdoor | | |
| location | | ilidooi / Odidooi | | |
| Mounting | | Floor stand | | |
| method | FIOOI Stariu | | | |
| Operating | | Charge: 0 to 50°C | | |
| temperature | | Discharge: -20 to 50° | С | |
| Degree of | | IDEE | | |
| protection | | IP55 | | |
| Allowable rela- | | | | |
| tive humidity | | 0% to 95% no condens | ing | |
| range | | | | |
| Max. operating | | 2000 m | | |
| altitude | | 2000 111 | | |
| Cooling | | Natural convection | | |
| method | | Natural Convection | | |
| Warranty ² | | 10 Years | | |
| Expansion | Up to 4 units in parallel(need extra Combiner box) | | | |
| adaptation | Op to 4 units in parallel (need extra Combinel box) | | | |

- 1: Test conditions: 25°C,100% depth of discharge (DOD), 0.2C charge and discharge.
- 2: Refer to battery warranty card for conditional application.

table 9-2 Technical parameters of high voltage LFP battery(SBR192 / SBR224 / SBR256).

| Parameters | SBR192 | SBR224 | SBR256 |
|------------------------------|---------------|------------------------|---------------|
| System Data | | | |
| Battery Type | | LiFePO4 Prismatic Cell | |
| Battery Module | | 3.2 kWh, 33 kg | |
| Energy (usable) ¹ | 19.2 kWh | 22.4 kWh | 25.6 kWh |
| Nominal voltage | 384 V | 448 V | 512 V |
| Operating voltage | 300 V – 438 V | 350 V – 511 V | 400 V – 584 V |
| Rated DC power | 11.52 kW | 13.44 kW | 15.36 kW |
| Max. charge/dis- | 42.44.144 | 45.00 IAM | 47.50 1/1/ |
| charge power | 13.14 kW | 15.33 kW | 17.52 kW |

User Manual 9 Appendix

| Parameters | SBR192 | SBR224 | SBR256 | | |
|-----------------------|---|---------------------------|------------------|--|--|
| Max. charging / dis- | | | | | |
| charging current: | 30 A | | | | |
| continuous | | | | | |
| Max. charging / dis- | | | | | |
| charging current: | | 42 A | | | |
| Depth of Discharge | N | Max. 100% DOD(settabl | e) | | |
| Short circuit current | | 3500 A | | | |
| Display | SC | C indicator, Status indic | ator | | |
| Communication | | CAN | | | |
| interface | | CAN | | | |
| Protection | | | | | |
| Over / under voltage | | Yes | | | |
| protection | | 165 | | | |
| Over current | | Yes | | | |
| protection | | 165 | | | |
| Over / under tem- | | Voc | | | |
| perature protection | | Yes | | | |
| DC breaker | | Yes | | | |
| General Data | | | | | |
| Dimensions | 625 * 935 * 330 | 625 * 1065 * 330 | 625 * 1195 * 330 | | |
| (W*H*D) | mm | mm | mm | | |
| Weight | 213 kg | 246 kg | 279 kg | | |
| Installation location | | Indoor / Outdoor | | | |
| Mounting method | | Floor stand | | | |
| Operating | | Charge: 0 to 50°C | | | |
| temperature | | Discharge: -20 to 50°C | | | |
| Degree of protection | | IP55 | | | |
| Allowable relative | | 20/ 1 250/ | | | |
| humidity range | 0% to 95% no condensing | | | | |
| Max. operating | | | | | |
| altitude | 2000 m | | | | |
| Cooling method | Natural convection | | | | |
| Warranty ² | | 10 Years | | | |
| Expansion | | | | | |
| adaptation | Up to 4 units in parallel (need extra Combiner box) | | | | |
| <u> </u> | | | | | |

^{1:} Test conditions: 25°C,100% depth of discharge (DOD), 0.2C charge and discharge.

^{2:} Refer to battery warranty card for conditional application.

9 Appendix User Manual

table 9-3 Technical parameters of battery combiner box(SJR-04).

| Type designation | SJR-04 |
|--|----------------------------------|
| Max. working voltage | 600 Vdc |
| Max. working current | 30 A |
| Max. battery parallel inputs | 4 |
| Dimensions (W*H*D) | 350*336*125 mm |
| Weight | 5.6 kg |
| Environment temperature | -20 to 50°C |
| Environment humidity (non-condensing) | 0~95% |
| Ingress protection (IP) rating | IP65 |
| Communication interface | RJ45 (PCS) , Connector (Battery) |
| Communication mode CAN , RS485 (reserved) | |
| Input terminal type | MC4 (Battery) |
| Output terminal type | Sunclix (PCS) |
| Installation location | Indoor / Outdoor |
| Mounting method | wall-mounted |
| Max. operating altitude | 2000 m |
| Cooling method | Natural convection |

9.2 Quality Assurance

When product faults occur during the warranty period, SUNGROW will provide free service or replace the product with a new one.

Evidence

During the warranty period, the customer shall provide the product purchase invoice and date. In addition, the trademark on the product shall be undamaged and legible. Otherwise, SUNGROW has the right to refuse to honor the quality guarantee.

Conditions

- After replacement, unqualified products shall be processed by SUNGROW.
- The customer shall give SUNGROW a reasonable period to repair the faulty device.

Exclusion of Liability

In the following circumstances, SUNGROW has the right to refuse to honor the quality guarantee:

User Manual 9 Appendix

- The free warranty period for the whole machine/components has expired.
- · The device is damaged during transport.
- · The device is incorrectly installed, refitted, or used.
- The device operates in harsh conditions beyond those described in this manual.
- The fault or damage is caused by installation, repairs, modification, or disassembly performed by a service provider or personnel not from SUNGROW.
- The fault or damage is caused by the use of non-standard or non-SUNGROW components or software.
- The installation and use range are beyond stipulations of relevant international standards.
- · The damage is caused by unexpected natural factors.

For faulty products in any of above cases, if the customer requests maintenance, paid maintenance service may be provided based on the judgment of SUNGROW.

9.3 Contact Information

Should you have any question about this product, please contact us.

We need the following information to provide you the best assistance:

- · Model of the device
- · Serial number of the device
- · Date of the device
- Fault code/name

China (HO)

· Brief description of the problem

| China (HQ) | Australia |
|-------------------------------|-----------------------------------|
| Sungrow Power Supply Co., Ltd | Sungrow Australia Group Pty. Ltd. |
| Hefei | Sydney |
| +86 551 65327834 | +61 2 9922 1522 |
| service@sungrowpower.com | service@sungrowpower.com.au |
| | |
| Brazil | France |
| Brazil Sungrow Do Brasil | France Sungrow France |
| | |
| Sungrow Do Brasil | Sungrow France |

A . . . 4.. . 1! .



9 Appendix User Manual

| Germany, Austria, Switzerland | Greece |
|---------------------------------|----------------------------------|
| Sungrow Deutschland GmbH | Service Partner – Survey Digital |
| Munich | +30 2391052757 |
| +49 (0)89 1307 2620 | service@sungrow-emea.com |
| service@sungrow-emea.com | |
| India | Italy |
| Sungrow (India) Private Limited | Sungrow Italy |
| Gurgaon | Verona |
| +91 080 41201350 | +39 0800 974739 (Residential) |
| service@in.sungrowpower.com | +39 045 4752117 (Others) |
| | service@sungrow-emea.com |
| Japan | Korea |
| Sungrow Japan K.K. | Sungrow Power Korea Limited |
| Tokyo | Seoul |
| + 81 3 6262 9917 | +82 70 7719 1889 |
| service@jp.sungrowpower.com | service@kr.sungrowpower.com |
| Malaysia | Philippines |
| Sungrow SEA | Sungrow Power Supply Co., Ltd |
| Selangor Darul Ehsan | Mandaluyong City |
| +60 19 897 3360 | +63 9173022769 |
| service@my.sungrowpower.com | service@ph.sungrowpower.com |
| Thailand | Spain |
| Sungrow Thailand Co., Ltd. | Sungrow Ibérica S.A.U. |
| Bangkok | Mutilva |
| +66 891246053 | +34 948 05 22 04 |
| service@th.sungrowpower.com | service@sungrow-emea.com |
| Romania | Turkey |
| Service Partner - Elerex | Sungrow Deutschland GmbH Turkey |
| service@sungrow-emea.com | Istanbul |
| | +90 216 663 61 80 |
| | service@sungrow-emea.com |
| UK | U.S.A, Mexico |
| Sungrow Power UK Ltd. | Sungrow USA Corporation |
| Milton Keynes | Phoenix |
| +44 (0) 01908 414127 | +1 833 747 6937 |
| service@sungrow-emea.com | techsupport@sungrow-na.com |

User Manual 9 Appendix

| Vietnam | Belgium, Netherlands and Luxembourg |
|-----------------------------|--|
| Sungrow Vietnam | (Benelus) |
| Hanoi | +31 853 018 234 (only for Netherlands) |
| +84 918 402 140 | service@sungrow-emea.com |
| service@vn.sungrowpower.com | |
| Poland | |
| +48 221530484 | - |
| service@sungrow-emea.com | |